

# LOGICAL AND CONTROL INSTRUCTIONS

Example: CMP B or CMP M

Compare immediate with accumulator

CPI 8-bit data The second byte (8-bit data) is compared with the contents of the accumulator. The values being compared remain unchanged. The result of the comparison is shown by setting the flags of the PSW as follows:

if (A) < data: carry flag is set

if (A) = data: zero flag is set

if (A) > data: carry and zero flags are reset

Example: CPI 89H

Logical AND register or memory with accumulator ANA R The contents of the accumulator are logically ANDed with M the contents of the operand (register or memory), and the result is placed in the accumulator. If the operand is a memory location, its address is specified by the contents of HL registers. S, Z, P are modified to reflect the result of the operation. CY is reset. AC is set.

Example: ANA B or ANA M

Logical AND immediate with accumulator ANI 8-bit data The contents of the accumulator are logically ANDed with the 8-bit data (operand) and the result is placed in the accumulator. S, Z, P are modified to reflect the result of the operation. CY is reset. AC is set.

Example: ANI 86H

Exclusive OR register or memory with accumulator XRA R The contents of the accumulator are Exclusive ORed with M the contents of the operand (register or memory), and the result is placed in the accumulator. If the operand is a memory location, its address is specified by the contents of HL registers. S, Z, P are modified to reflect the result of the operation. CY and AC are reset.

Example: XRA B or XRA M

Exclusive OR immediate with accumulator XRI 8-bit data The contents of the accumulator are Exclusive ORed with the 8-bit data (operand) and the result is placed in the accumulator. S, Z, P are modified to reflect the result of the operation. CY and AC are reset.

Example: XRI 86H

Logical OR register or memory with accumulator ORA R The contents of the accumulator are logically ORed with M the contents of the operand (register or memory), and the result is placed in the accumulator. If the operand is a memory location, its address is specified by the contents of HL registers. S, Z, P are modified to reflect the result of the operation. CY and AC are reset.

Example: ORA B or ORA M

Rotate accumulator left

RLC none Each binary bit of the accumulator is rotated left by one position. Bit D7 is placed in the position of D0 as well as in the Carry flag. CY is modified according to bit D7. S, Z, P, AC are not affected.

Example: RLC

Rotate accumulator right

RRC none Each binary bit of the accumulator is rotated right by one position. Bit D0 is placed in the position of D7 as well as in the Carry flag. CY is modified according to bit D0. S, Z, P, AC are not affected.

Example: RRC

Rotate accumulator left through carry

RAL none Each binary bit of the accumulator is rotated left by one position through the Carry flag. Bit D7 is placed in the Carry flag, and the Carry flag is placed in the least significant position D0. CY is modified according to bit D7. S, Z, P, AC are not affected.

Example: RAL

Rotate accumulator right through carry

RAR none Each binary bit of the accumulator is rotated right by one position through the Carry flag. Bit D0 is placed in the Carry flag, and the Carry flag is placed in the most significant position D7. CY is modified according to bit D0. S, Z, P, AC are not affected.

Example: RAR

Complement accumulator

CMA none The contents of the accumulator are complemented. No flags are affected.

Example: CMA Complement carry CMC none The Carry flag is complemented. No other flags are affected.

Example: CMC

Set Carry

STC none The Carry flag is set to 1. No other flags are affected.

Example: STC

Logical OR immediate with accumulator

ORI 8-bit data The contents of the accumulator are logically ORed with the 8-bit data (operand) and the result is placed in the accumulator. S, Z, P are modified to reflect the result of the operation. CY and AC are reset.

Example: ORI 86H

### 1.5.5 CONTROL INSTRUCTIONS

#### No operation

**NOP** none No operation is performed. The instruction is fetched and decoded. However no operation is executed.

Example: NOP

#### Halt and enter wait state

**HLT** none The CPU finishes executing the current instruction and halts any further execution. An interrupt or reset is necessary to exit from the halt state.

Example: HLT

#### Disable interrupts

**DI** none The interrupt enable flip-flop is reset and all the interrupts except the TRAP are disabled. No flags are affected.

Example: DI

#### Enable interrupts

**EI** none The interrupt enable flip-flop is set and all interrupts are enabled. No flags are affected. After a system reset or the acknowledgement of an interrupt, the interrupt enable flipflop is reset, thus disabling the interrupts. This instruction is necessary to reenable the interrupts (except TRAP).

Example: EI

Source : <http://nprcet.org/e%20content/Misc/e-Learning/IT/IV%20Sem/CS%202252-Microprocessors%20and%20Microcontrollers.pdf>